



CP.B24ESA



100%
Made in Italy



APPLICATION

1 actuator for sliding gates, series BULL424ESA and BULL624ESA

CONTROL UNIT POWER SUPPLY

230 Vac

MOTORS POWER SUPPLY

24 Vdc 80W


MAIN FUNCTIONS

Integrated LCD display | Integrated 433.92 MHz 64-code radio receiver with 3 encoding systems (Advanced Rolling Code, Rolling Code, Fixed Code) | Integrated ESA SYSTEM for energy savings | Removable terminal boards | Automatic, semi-automatic and deadman's logic | Motor limit switch inputs | Separate photocell inputs in opening-closing and photocell active in closing phases | Pedestrian, step by step and stop inputs | Input for N.C or 8K2 sensitive edge | Two outputs for configuration as gate open indicator, service light, second radio channel or area light | Photocell testing | Autosetting of operating parameters | Electronic torque adjustment with automatic calculation for each point in the stroke (STC SYSTEM) | Anti-crushing safety thanks to amperometric detection and encoder management | Adjustable slow-downs | Advantouch system to configure parameters and manage radio transmitters | Number of maneuvers | Programming access password | Maintenance warning



DA.2S

Electronic board that allows synchronised movement of 2 automation devices (opposed sliding gates).



BULL24.CBY

Accessory with CBY.24V battery charger, 1.2 Ah batteries and support bracket.

AUTOMATISMI BENINCA SpA • Via del Capitello, 45 • 36066 Sandrigo (VI) ITALY • T +39 0444 751030 • sales@beninca.com

